

1. Differential Probes for High Voltage Power Measurement

| Model No. | Bandwidth | Common Mode | Differential | Attenuation | Accuracy | Input R & C |
|-----------|-----------|-------------|-----------------|---------------|----------|-------------|
| SI-9010 | 70MHz | ±7000V | ±700V, ±7000V | 1/100, 1/1000 | ±2% | 10MΩ//7pF |
| SI-9020 | 70MHz | ±7000V | ±1400V, ±14000V | 1/200, 1/2000 | ±2% | 10MΩ//7pF |
| SI-9010A | 70MHz | ±7000V | ±700V, ±7000V | 1/100, 1/1000 | ±2% | 10MΩ//7pF |

2. Differential Probes for Power Measurement

| Model No. | Bandwidth | Common Mode | Differential | Attenuation | Accuracy | Input R & C |
|-----------|-----------|-------------|---------------|---------------|----------|-------------|
| SI-9001 | 25MHz | ±700V | ±70V, ±700V | 1/10, 1/100 | ±2% | 4MΩ//5.5pF |
| SI-9002 | 25MHz | ±1400V | ±140V, ±1400V | 1/20, 1/200 | ±2% | 4MΩ//5.5pF |
| SI-50 | 50MHz | ±700V | ±70V | 1/10 | ±1% | 1.6MΩ//7pF |
| SI-51 | 50MHz | ±700V | ±700V | 1/100 | ±1% | 1.6MΩ//7pF |
| SI-9101 | 100MHz | ±700V | ±70V, ±700V | 1/10, 1/100 | ±2% | 4MΩ//5.5pF |
| SI-9110 | 100MHz | ±1400V | ±140V, ±1400V | 1/100, 1/1000 | ±2% | 4MΩ//7pF |

3. Differential Prob for Small Signals

| Model No. | Bandwidth | Common Mode | Differential | Attenuation | Accuracy | Input R & C |
|-----------|-----------|-------------|--------------|-------------|----------|-------------|
| SI-200 | 200MHz | ±60V | ±20V | 1/10 | ±1% | 500kΩ//7pF |

4. Differential Probe for High Bandwidth Measurement

| Model No. | Bandwidth | Common Mode | Differential | Attenuation | Accuracy | Input R & C |
|-----------|-----------|-------------|--------------|-------------|----------|-------------|
| SI-800 | 800MHz | ±30V | ±15V | 1/10 | ±2% | 100kΩ//2pF |