


Ø 4 mm-Einpressbuchsen

EB4




PEWA
Messtechnik GmbH
Weidenweg 21
58239 Schwerte
Tel.: 02304-96109-0
Fax: 02304-96109-88
E-Mail: info@pewa.de
Homepage: www.pewa.de

Ø 4 mm Press-in Sockets



Insulated Ø 4 mm rigid socket. Machined brass.
The socket is pressed into predrilled panels of plastic, metal etc.
Flat connecting tab 4.8 mm x 0.8 mm.

Douilles Ø 4 mm à emmancher



MA 103

Montagebohrung
Panel drilling
Perçage de panneau



Douille rigide Ø 4 mm, isolée. Laiton décollété.
A emmancher dans des perçages de panneaux ou de boîtiers plastiques, métalliques...
Raccord plat 4,8 mm x 0,8 mm.

Isolierte, starre Ø 4 mm-Buchse. Messingdreh-
teil. Montage durch Einpressen in Bohrungen
von Platten oder Gehäusen aus Kunststoff, Me-
tall etc. **Anschluss:**
Flachstecker 4,8 mm x 0,8 mm.

Typ Type Type	Best.-Nr. Order No. N° de Cde	Bemessungsspannung / -strom Rated voltage / current Tension / intensité assignée	Einzelteile: Isolierteil / Buchse Component parts: Insulator / Socket Pièces détachées : Isolant / Douille	*Farben *Colours *Couleurs
---------------------	-------------------------------------	--	--	----------------------------------

EB4

23.1013-*

30 V_{AC} ~ 60 V_{DC} / 25 A

I-EB4, 23.5013-* / B-EB4, 23.5012

Au



Zubehör

Einpressdorn: MB4 (→ Seite 193)
Flachsteckhülse: FSH4,8x0,8 (→ Seite 192)

Accessories

Press-in tool: MB4 (→ page 193)
Flat connecting receptacle: FSH4,8x0,8 (→ page 192)

Accessoires

Outil d'emmanchement : MB4 (→ page 193)
Cosse plate : FSH4,8x0,8 (→ page 192)