

# Passive 10X Voltage Probe

## THP0301-Y, THP0301-B, THP0301-M, THP0301-G Data Sheet



### Features & Benefits

- 300 MHz Bandwidth for the THS3000 Series Handheld Oscilloscopes
- 10X Attenuation
- 1.2 m Length

### Applications

- Low-frequency Computer and Telecom Measurements
- Power Supplies
- Low-frequency Amplifiers
- Inverter Design
- Power Conversion

### THP0301 Passive Voltage Probes

The THP0301 probes are 300 MHz, 10X passive voltage probes with 10 M $\Omega$  input resistance. These probes are for use with the THS3000 Series oscilloscopes and are color coded to match the oscilloscope's channel input connectors, front-panel channel selector buttons, and the displayed waveforms.

### Safely Measure from mV to kV

The THP0301 probes have a CAT III safety rating which matches the safety rating on the THS3000 Series oscilloscopes enabling you to safely measure voltage ranges from mV to kV. You'll be able to measure anything from micro-electronics to heavy-duty medium-voltage electrical applications, making it possible to obtain accurate measurements in mixed-signal environments with separate ground references.

For a complete list of compatible oscilloscopes, refer to the Tektronix Oscilloscope Probe & Accessory Selector Tool at <http://www.tek.com/probes>.



**PEWA**  
Messtechnik GmbH

Weidenweg 21  
58239 Schwerte

Tel.: 02304-96109-0  
Fax: 02304-96109-88  
E-Mail: [info@pewa.de](mailto:info@pewa.de)  
Homepage : [www.pewa.de](http://www.pewa.de)



Characteristics

Characteristic	Description
Bandwidth	DC to 300 MHz
Probe Length	1.2 m
Compensation Range	10 pF to 22 pF
Input Capacitance	11 pF
Input Resistance	10 MΩ
Maximum Input Voltage	300 V CAT III

Ordering Information

Model	Description
THP0301-Y	(Yellow) DC to 300 MHz, 10X high-voltage probe*1
THP0301-B	(Blue) DC to 300 MHz, 10X high-voltage probe*1
THP0301-M	(Magenta) DC to 300 MHz, 10X high-voltage probe*1
THP0301-G	(Green) DC to 300 MHz, 10X high-voltage probe*1

**Includes:** Push-on hook clip, push-on reference contact, alligator ground, un-insulated push-on BNC adapter (020-3085-xx).

\*1 One of each probe is included as a standard accessory with the THS3000 Series oscilloscopes.

Optional Accessories

Accessory	Description
020-3085-xx	Probe Accessory Replacement Kit

